



Schneider Electric Easy UPS 1 Ph BVS Series

For our home and small office customers Schneider Electric delivers a new category of UPSs designed for the essential power protection needs even in the most unstable power conditions, introducing Easy UPS 1 Ph BVS Series. Easy UPS 1 Ph BVS Series is a versatile, high quality UPS developed to handle inconsistent power conditions.

Schneider Electric Easy UPS 1 Ph BVS Series is a versatile UPS developed to handle inconsistent power conditions while also delivering the quality millions trust around the world.



www.schneider-electric.com

Life Is On

Schneider
Electric



Schneider Electric Easy UPS BVS Series Standard Features

Flexible design for both high and low powered devices

Capable of powering low power devices such as your modem, router, or VOIP as well as high power devices such as PCs, and gaming consoles.

Stay connected for hours, not minutes

Power your home router and/or modem allowing you to maintain your internet connection after safely shutting down your PC or other high power devices.

Automatic Voltage Regulation (AVR)

Corrects voltage dips and surges to safe levels which is especially important for regions with poor power. This also saves battery life by correcting sustained voltage fluctuations without losing battery power.

Reliable surge protection

Protects your valuable electronic devices against damaging lightning, surges and spikes.

Wall mounting sockets

Keyhole sockets for mounting the UPS in structured wiring closets, behind desks, in basements, and garages.

Wide outlet spacing

Allows you to connect bulky transformers without blocking other outlets.

Compact size

Accommodates installation in a variety of environments

Intelligent off-mode charging

Continues to charge the battery even when the UPS is off

Cold start function

Allows you to reboot the UPS even when there is no utility power available

Easy to use

One step battery connector

Battery self diagnosis

Alerts users with the appropriate alarm for battery conditions

2-Year warranty and always on customer service

Customer service is always there when you need it via phone support, online forums, and live chats with support agents.

Life Is On

Schneider
Electric

UPS Model	BVS500I-AZ	BVS800I-AZ
Output		
Power Capacity	300 W / 500 VA	450 W / 800 VA
Output Voltage on Battery	230VAC +/- 10%	
Output Frequency Range (sync mode)	50 Hz or 60 Hz +/- 1 Hz	
Topology and output waveform	Line interactive	
Output Connections	Australian Outlet	
Input		
Input Voltage Range	170-280 (V)	
AC Input Fuse	5A	10A
Cord Length	1.5 (m)	
Input Connection	Australian	
Batteries		
Battery Type (maintenance-free)	12 V / 4.5 AH X1	12 V / 7 Ah x 1
Typical Recharge Time	6-8 hours	
Runtime Estimates		
120 W Runtime (min)	5	15
180 W Runtime (min)	3	9
240 W Runtime (min)	0.5	2.5
Physical & Warranty		
Dimensions	9.25 cm x 16.05 cm x 30.5 cm	
Net weight	3.9 kg	5.3 kg
Warranty	2 Years	

Life Is On

Schneider
Electric